

SPEC SHEET

RGB LED Linear Wall Washer

STDCLEDRGB

- Suitable for Indoor or Outdoor - Waterproof
- Low Heat Emission
- No Ultraviolet or Infrared Radiation
- Anodized Aluminum Body
- UL & ETL Listed
- 3-Year limited warranty

Description

Indoor/Outdoor L.E.D. RGB Wall Washer. 40" long unit. 30 high power diodes cased in a sturdy aluminum, waterproof housing. Great for casting vibrant colors onto large structures. Can be used as a standalone unit or link multiple fixtures. Internal settings allow users to create basic scenes without the need for a DMX operator. For more custom situations, connect fixture(s) to a DMX512 compatible controller.

Specifics:

Voltage:	85 - 165VAC
Output:	36 Watts
Lumens:	44 Red, 70 Green, 15 Blue (single diode)
Beam Angle:	40-60°
Dimensions:	24" L x 4" W x 3" H 40" L x 4" W x 3" H
Lifespan:	± 30,000 - 50,000 hours
Note:	3-Pin connectors DMX512 Compatible



30 LED Diodes

Manual or DMX 512 Driven

- **Manual mode:** User can easily set-up lighting effects by adjusting the pre-programmed, internal settings on fixture
- **DMX512 mode:** Users can match Pantone colors & create custom lighting scenes using a DMX512 compatible operating board



RGB Internal Settings:

LINEAR RGB WALL WASH INTERNAL SETTINGS
USE UP / DOWN BUTTONS TO SELECT MODE
PRESS MENU BUTTON TO ACCESS MODE SETTING
USE UP / DOWN BUTTONS TO ADJUST MODE SETTING
PRESS MENU BUTTON TO RETURN TO MODE SELECTION

MODE	MODE SETTINGS
A-1	FUNCTION - PREPROGRAMMED 7 COLOR FADE-IN/FADE-OUT CYCLE * Press MENU. Use UP / DOWN buttons to set speed of Fade-In / Fade-Out Cycle
A-2	FUNCTION - PREPROGRAMMED 7 COLOR FLASH CYCLE (NO FADE-IN / FADE-OUT) * Press MENU. Use UP / DOWN buttons to set speed of Flash Cycle
A-R	FUNCTION - ADJUST LEVEL OF RED SATURATION Press MENU. Use UP / DOWN buttons to set the level of RED light displayed
A-G	FUNCTION - ADJUST LEVEL OF GREEN SATURATION Press MENU. Use UP / DOWN buttons to set the level of GREEN light displayed
A-B	FUNCTION - ADJUST LEVEL OF BLUE SATURATION Press MENU. Use UP / DOWN buttons to set the level of BLUE light displayed
A-D	FUNCTION - ADJUST BRIGHTNESS Press MENU. Use UP / DOWN buttons to set the brightness level (001-Low / 255-High)
A-5	FUNCTION - STATIC COLOR FLASH-ON / FLASH-OFF Press MENU. Use UP / DOWN buttons to set speed of Static Color Flash Cycle (000-
ADR	FUNCTION - DMX ADDRESS (SET FOR USE WITH DMX CONTROLLER) Press MENU. Use UP / DOWN buttons to set DMX ADDRESS (001 - MASTER / SLAVE
* PREPROGRAMMED COLORS - RED, GREEN, BLUE, YELLOW, CYAN, PURPLE, WHITE	

