

# LED RGB COLOR CHANGING FLEX NEON LIGHT KIT

SPECIFICATION SHEET

ORDER SKUs:

STFXRGB120VKIT



## Features:

- Sold in 164 Ft (50 meters) Roll with Plug N Play Controller and 44 Key IR remote Included.
- 44 Key IR remote can control wireless within 16 Ft (5 meters) range.
- The max run with Plug N Play Controller is 98 Ft (30 meters).
- For a custom cut length price quote, please email inquiry to sales@step1dezigns.com.
- High intensity LED and continuously line to attract attention
- Safe low heat operation; cool to the touch
- High visibility, even in direct other light
- Fully enclosed electronics for wet environments

## Installation:




Step 1. Cut RGB FLEX NEON at its cut marking point.



Step 2. Align 4-Pin Power to Strip Connector with the LED RGB Neon strip's connector points.



Step 3. Insert the 4-Pin connector into the RGB FLEX Neon strip.



Step 4. Align the 4-Pin connector and insert into the LED RGB controller connector.

## Description:

Step 1 Dezigns Color Changing RGB LED Flex Neon kit is a superior quality product that allows you to achieve the same lighting effects as the standard glass neon tubes lights. It is flexible, reliable, bright, easy to bend and install. It can be used in many applications including edges and corners and can be custom cut to required lengths. Installation is simple due to its versatility and flexibility. With an operating voltage of 110v AC and its unique construction the LED RGB Flex-Neon is safe for indoor or outdoor environments.

## Specification:

<b>Voltage:</b>	120V AC
<b>Wattage:</b>	4.4w per ft.
<b>LED Color:</b>	RGB
<b>LED Chip Size:</b>	5050
<b>Dimmable:</b>	No
<b>Dimension:</b>	165Ft (50 meters) per kit
<b>Cut Length:</b>	Cuttable every 19.5" at the cut marking 0.55" W x 1.02" H
<b>Dimension:</b>	Up to 100,000 hours
<b>Lifespan:</b>	Wet Location IP65
<b>Environment:</b>	1x Plug N Play Controller
<b>Included items:</b>	1x IR Remote
	1x End Cap
	1x Power to Strip 4-Pin Connector

**Additional Items:** [CONTROLLER with REMOTE DIRECT CONNECTOR](#)  
[6 in. JUMPER](#)  
[END CAP](#)  
[MOUNTING CHANNEL](#)

